I.I Keys

- Accept an incoming call

- To dial the number focused on the screen

End Key (هي)

- Power on (long press)
- Return back to idle from any other state
- Turn off the backlight and lock the screen (short press in
- Long press in idle to access 'quick profile + power off'
- Navigation keys (in idle screen):
- Up to message
- Down to Camera - Left to alarm
- Right to Bluetooth menu

Central key (

- Open Main Menu in idle
- Confirm/ok/select in other state Play/pause key (side middle key)
- Play/pause music
- Volume keys (side keys)
- Adjust general volume (short press)
- Go or return to previous/next song (long press)

I.2 Main screen icons (1)

Battery charge level.

- Vibrate alert: your cellphone vibrates, but does not ring or been with the exception of the alarm
- Bluetooth status (Blue Activated).
 - Bluetooth status (Connected to an audio device)
- Headset connected
- (1) The icons and illustrations in this guide are provided for informational purposes only.

Keypad locked.

Call forwarding activated: your calls are forwarded

Alarm clock or appointment(s).

Level of network reception

Voicemail message or PUSH message arrived.

Unanswered calls

Radio is on

Web alerts (I) RM Roaming

ΞΪ Memory card scanning in progress.

Memory card scanning completed. Line switching (2): indicates the selected line

G GPRS attached

G GPRS connecting Music player active.

Message receipt in progress

Sending a message.

Silence mode: your cellphone does not ring, beep or

Message unread

(1) Depending on your network operator

Message list is full: your cellphone cannot accept any new messages. You must access the message list and delete at 2.3 Power off your cellphone least one message on your SIM card.

Flight mode.

 \bowtie

Bluetooth headset connected

(2) Contact your network operator to check service availability.

cellphone is equipped with FM radio (1) with RDS functionality

2.1 Let's go

Removing and installing the back cover







serting and installing the battery, SIM card





Place the SIM card with the chip facing downwards and slide it into its 3.3 Receiving a call housing. Make sure that it is correctly inserted. To remove the card, press it and slide it out.

2.2 Power on your cellphone

Hold down the ⋄✓ key until the cellphone powers on.

Hold down the ೨১ key until the pop-up "Profile tab" appears, then select "Power off" and confirm.

3.1 Making a Call

Dial the desired number then press the 📞 key to place the call. If You can access your call memory by pressing 📞 from the idle

you n

To hang up the call, press the y key.

Making an emergency call

without a SIM card and without typing the PIN code (1).

3.2 Calling your voicemail (2)

works like an answering machine that you can consult at any time. To GPRS counter, Beep duration. access your voicemail, hold down key.

When you receive an incoming call, press the \cup key to talk and forwarding, Call barring, Caller ID, Auto redial. then hang up using the 🏽 🗓 🗸 key.

3.4 Available functions during the call

During a call, you can use your directory, short messages, etc. without

Calls

ou make a mistake, you can delete the incorrect digits by pressing the screen. Choose the option of the desired list: Outgoing call(s), Missed call(s), Answered call(s).

4.2 My numbers

If your cellphone is covered by the network, dial emergency number Type in or modify your cellphone number or the number to access and press the \cup key to make an emergency call. This works even your voicemail and confirm by clicking. Your cellphone number is usually written on your SIM card.

4.3 Billings

Your voicemail is provided by your network to avoid missing calls. It You can access different items with this option: Amount, Duration.

4.4 Call settings (1)

You can access a number of items with this option: Call waiting, Call

(1) Contact your network operator to check service availability.

(i) Depends on local regulations (2) Contact your network operator to check service availability.

Directory.....


5.1 Consulting your directory list In Idle interface, click 🔼 icon to access the contacts.

5.2 Create contact

other compatible cellphones.

Select the contacts list in which you wish to add a contact to, press the "Options" softkey, select "Create contact" then





You can create, edit and receive SMS and MMS⁽¹⁾ with this cellphone.

6.1 Create text/multimedia message (1)

You can click M in idle interface to create a message. Or select "Messages" from the Main Menu to create text/multimedia messages. You can type a message, but you can also modify a predefined message Access to main menu "Applications" and select "Music player". You Bookmarks

writing a message, select "Options" to access all the messaging You can save standard messages to Drafts or Templates (MMS only).

Camera

- send them in a multimedia message (MMS) to a cellphone or an email address:
- customize your main screen;

7.2 My creations

- transfer them by data cable or microSD card to your computer;

Select o access the function from main menu.

MMS enables you to send images, photos, animations and sounds to This feature stores all the photos captured by your cellphone.

Applications.....

in "Templates" or customize your message by adding pictures, will have full flexibility of managing music both on your cellphone and Recent pages • Pages which you recently browsed. photos, sounds, titles, etc. (only available while editing an MMS). While memory card.

You can use the application as a traditional radio with saved channels Your cellphone is fitted with a camera for taking photos that you can or with parallel visual information related to the radio program on the use in different ways store them in your "File manager": listen to it while running other applications.

8.3 Image viewer select them as incoming call image to a contact in your directory; A library links to the pictures in "My creations" and "My images" in

Web 🍵

information such as weather conditions, news, sport and download new ringtones, wallpapers, music. Homepage

- Offline pages

MMS. Bluetooth.

Profiles

· Launch the Web browser with the homepage of

Internet is a mobile internet portal service which allows you to obtain 10.4 Calendar

- the default profile.
- Access your favorite sites
- Go to LIRI Enter the LIRI of Web site
- Pages available for offline viewing. Customize your Web access.

display if you tune to stations that offer Visual Radio service. You can Contact your network operator to check service availability.

Your cellphone has a built-in alarm clock with a snooze feature.

10.2 Alarm

cellphone to be shown in list, slide, or thumbnail, set as Wallpaper, 10.3 Bluetooth Screen saver, Power on/off display, and Contact ID, or sent by To use your cellphone with a Bluetooth device, you need to proceed 11.3 My videos

() Tools..... ==

- in two steps: - Pair and register the device to your cellphone,
- Select it to use hands-free communication. Only one Bluetooth be connected during the communication.

Once you enter this menu from "Tools", there is a monthly-view Store files of unsupported format. calendar for you to keep track of important meetings, appointments, etc. Days with events entered will be marked in color.

10.5 Calculator

Enter a number, select the type of operation to be performed, and II.7 Memory status enter the second number, then press every key to display the result. To Indicates how much space is used and how much is currently free on return to the main screen, click area.

You can create a Text note or Voice memo by accessing "Memo"

10.7 World clock

may view up to 3 cities at one time (Options\Set as my city). Also, you can add a maximum of 10 new cities to the list (Options\Add).

File manager

message alert, power on/off ringtone or an alarm and scheduler.

II.2 My images

You can select an image or a photo as wallpaper, ON/OFF screen, or assign it to a contact in the directory.

The "My videos" album contains all video clips downloaded to the phone or memory card.


This feature stores all the photos captured by your cellphone.

11.5 Other files

11.6 Memory card You can access all files stored in memory card here.

your cellphone and memory card (if any).

7 Settings



3 Latin input mode/character table(1)

To write messages, there are two writing methods:

This mode allows you to type text by choosing a letter or a sequence

- Normal

- Predictive with the 7i mode This mode speeds up the writing of your text.

Press the key once and the word will be modified each time you press a key. As you go on, the word will keep changing.

> Alcatel-Lucent and used under license by TCT Mobile Limited. All rights reserved © Copyright 2010

ALCATEL is a trademark of

TCT Mobile Limited. TCT Mobile Limited reserves the right to alter material or technical specification without prior notice.

(1) For specific languages as Chinese, please see specific input leaflets.



station in that particular area.

The quality of the radio depends on the coverage of the radio

10.6 Memo

The World clock shows current local time and the time in different cities. You

manufacturer disclaims any liability for damage, which may result as a consequence Over 55°C the legibility of the cellphone's display may be impaired, though this is of improper use or use contrary to the instructions contained herein.

*TRAFFIC SAFFTY:

Given that studies show that using a cellphone while driving a vehicle constitutes a Do not drop, throw or try to bend your cellphone. real risk, even when the hands-free kit is used (car kit headset...), drivers are Do not paint it. requested to refrain from using their cellphone when the vehicle is not parked. Use only batteries, battery chargers, and accessories which are recommended by devices may be prohibited or restricted in certain areas

When driving do not use your cellphone and headphone to listen to music or to the radio. Using a headphone can be dangerous and forbidden in some areas.

When switched on, your cellphone emits electromagnetic waves that can interfere Remember to make back-up copies or keep a written record of all important with the vehicle's electronic systems such as ABS anti-lock brakes or airbags. To information stored in your cellphone. ensure that there is no problem:

- deployment area.
- check with your car dealer or the car manufacturer to make sure that the car's electronic devices are shielded from cellphone RF energy.

CONDITIONS OF LISE

You are advised to switch off the cellphone from time to time to optimize its performance. . Switch the cellphone off before boarding an aircraft to avoid prosecution

Switch the cellphone off when you are in health care facilities, except in designated

areas. As with many other types of equipment now in regular use, cellphones can the following safety precautions: interfere with other electrical or electronic devices, or equipment using radio

Switch the cellphone off when you are near gas or flammable liquids Strictly obey all signs and instructions posted in a fuel depot, gas station, or chemical plant, or in any potentially explosive atmosphere

the cellphone you should hold it against the ear on the opposite side to the device,

To avoid hearing impairment, answer the call before holding your cellphone to your ear. Also move the handset away from your ear while using the "hands-free" option because the amplified volume might cause hearing damage.

without supervision.

When replacing the cover please note that your cellphone may contain substances that could create an allergic reaction.

Always handle your cellphone with care and keep it in a clean and dust-free place.

Safety and use Do not allow your cellphone to be exposed to adverse weather or environmental conditions (moisture, humidity, rain, infiltration of liquids, dust, sea air, etc.). The Do not allow your cellphone to be exposed to adverse weather or environmental • PRIVACY: We recommend that you read this chapter carefully before using your cellphone. The max value depends on device, materials and housing paint/texture).

temporary and not serious.

Do not open or attempt to repair your cellphone yourself

Check the laws and regulations on the use of wireless cellphones and their TCT Mobile Limited and its affiliates and are compatible with your cellphone model accessories in the areas where you drive. Always obey them The use of these. TCT Mobile Limited and its affiliates disclaim any liability for damage caused by the use of other chargers or batteries.

> Your cellphone should not be disposed of in a municipal waste. Please check local regulations for disposal of electronic products.

Some people may suffer epileptic seizures or blackouts when exposed to flashing - do not place your cellphone on top of the dashboard or within an airbag lights, or when playing video games. These seizures or blackouts may occur even if a person never had a previous seizure or blackout. If you have experienced seizures or blackouts, or if you have a family history of such occurrences, please consult your doctor before playing video games on your cellphone or enabling a flashing-lights feature on your cellphone. Parents should monitor their children's use of video games or other features that incorporate flashing lights on the cellphones. All persons should discontinue use and consult a doctor if any of the following symptoms occur: convulsion, eye or muscle twitching, loss of awareness, involuntary movements or disorientation. To limit the likelihood of such symptoms, please take

- Do not play or use a flashing-lights feature if you are tired or need sleep.
- Take a minimum of a 15-minute break hourly

Mobile Limited and its affiliates

Play in a well lit environment

Play at the farthest distance possible from the screen

When you play games on your cellphone, you may experience occasional discomfort In European Union countries: When the cellphone is switched on it should be kent at least 15 cm from any medical in your hands, arms, shoulders, neck, or other parts of your body. Follow these device such as a pacemaker, a hearing aid or insulin pump. In particular when using instructions to avoid problems such as tendinitis, carpal tunnel syndrome, or other sculoskeletal disorders:

- Take a minimum of a 15-minute break every hour of game playing.
- If your hands, wrists, or arms become tired or sore while playing, stop and rest for several hours before playing again.
- If you continue to have sore hands, wrists, or arms during or after playing, stop the game and see a doctor

Prolonged exposure to music at full volume on the music player may cause the listener's hearing impairment. Adjust the volume before placing INSTRUCTIONS headphones on or in your ear. Only use headphones recommended by TCT

note that you must respect the laws and regulations in force in your jurisdiction notographs and recording sounds with your cellphone. Pursuant to such laws and voices of other people or any of their personal attributes, and reproduce or distribute not work in another jurisdiction. They should be used for this purpose only. them, as this may be considered to be an invasion of privacy.

It is the user's sole responsibility to ensure that prior authorization be obtain essary, in order to record private or confidential conversations or take a photograph of another person; the manufacturer the seller or vendor of your cellphone (including the operator) disclaim any liability which may result from the

BATTERY AND ACCESSORIES.

Before removing the battery from your cellphone, please make sure that the cellphone is switched off.

- Observe the following precautions for battery use: Do not attempt to open the battery (due to the risk of toxic fumes and burns).
- Do not puncture disassemble or cause a short-circuit in a battery Do not burn or dispose of a used battery in the garbage or store i temperatures above 60°C.
- regulations. Only use the battery for the purpose for which it was designed. Never



This symbol on your cellphone, the battery and the accessories means their life:

- Collection hins at points of sale

They will then be recycled, preventing substances being disposed of in the ronment, so that their components can be reused.

These collection points are accessible free of charge. All products with this sign must be brought to these collection points.

In non European Union jurisdiction

Items of equipment with this symbol are not be thrown into ordinary bins if your are to be taken to collection points for them to be recycled.

In the United States you may learn more about CTIA's Recycling Program

CHARGERS

Home A.C. chargers will operate within the temperature range of 0°C to 40°C. manufacturer's recommended operating temperature range is -10°C to +55°C (the or other jurisdiction(s) where you will use your cellphone regarding taking. The chargers designed for your cellphone meet with the standard for safety of information technology equipment and office equipment use. Due to different ons, it may be strictly forbidden to take photographs and/or to record the applicable electrical specifications, a charger you purchased in one jurisdiction may

Characteristics of power supply (depending on the country)
ined, if Travel charger: Input: 100-240 V, 50/60 Hz, 0.15 A

Output : 5 V. 350 mA

Lithium 650 mAh · RADIO WAVES:

THIS CELLPHONE MEETS THE GOVERNMENT'S REQUIREMENTS FOR EXPOSURE TO RADIO WAVES.

Your cellphone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radio-frequency (RF) energy. These limits are part of comprehensive guidelines and establish permitted levels of RF for the receiver devices associated with the operation of a licensed radio service energy for the general population. The guidelines are based on standards that were (e.g. FM broadcast), they bear the following statement: developed by independent scientific organizations through periodic and thorough. This device compiles with Part 15 of the FCC Rules Operation is subject to the evaluation of scientific studies. These guidelines include a substantial safety margin condition that this device does not cause harmful interference. designed to ensure the safety of all persons, regardless of age and health.

exposure standard for cellphones employs a unit of measurement known as the This device complies with Part 15 of the FCC Rules. Operation is subject to the Ratteries must be disposed of in accordance with locally applicable environmental. Specific Absorption Rate or SAR The SAR limit set by public authorities such as the following two conditions: munications Commission of the US Government (FCC), or by Industry (I) this device may not cause harmful interference use damaged batteries or those not recommended by TCT Mobile Limited and/or its

Canada, is 1.6 W/kg averaged over 1 gram of body tissue. Tests for SAR are (2) this device must accept any interference received, including interference that conducted using standard operating positions with the cellphone transmitting at its may cause undesired operation. highest certified power level in all tested frequency bands.

Although the SAR is determined at the highest certified power level, the actual SAR avoid touching it or degrading it. that these products must be taken to collection points at the end of level of the cellphone while operating can be well below the maximum value. This is As mobile devices offer a range of functions, they can be used in positions other than because the cellphone is designed to operate at multiple power levels so as to use against your ear. In such circumstances the device will be compliant with the Municipal waste disposal centers with specific bins for these items of only the power required to reach the network. In general, the closer you are to a guidelines when used with headset or USB data cable. If you are using another wireless base station antenna, the lower the power output of the cellphone Before a cellphone model is available for sale to the public, compliance with national positions the cellphone at least 2cm away from the body. regulations and standards must be shown.

The highest SAR value for this model cellphone when tested is:

OT-706A: 1.19 W/Kg for use at the ear and 0.966 W/Kg for use close to the body. Obigo® While there may be differences between the SAR levels of various cellphones and at various positions, they all meet the government requirement for RF exposure. For body-worn operation, the cellphone meets FCC RF exposure guidelines provided that it is used with a non-metallic accessory with the handset at least 1.5 cm from the body Use of other accessories may not ensure compliance with FCC RF exposure guidelines. jurisdiction or your region has suitable recycling and collection facilities; instead they

The World Health Organization (WHO) considers that present scientific information does not indicate the need for any special precautions for use of cellphones. If individuals are concerned, they might choose to limit their own or their children's RF exposure by limiting the length of calls, or using "hands-free" devices to CAUTION: RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN keep cellphones away from the head and body. (fact sheet n° 193). Additional WHO INCORRECT TYPE. DISPOSE OF USED BATTERIES ACCORDING TO THE information about electromagnetic fields and public health are available on the following website: http://www.who.int/peh-emf

Note:This equipment has been tested and found to comply with the limits for a Class General information B digital device pursuant to part 15 of the ECC Rules These limits are designed to provide reasonable protection against harmful interference in a resid installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that On our Internet site, you will find our FAQ (Frequently Asked interference to radio or television reception, which can be determ equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

For other devices they hear the following statement

- Increase the separation between the equipment and receiver
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Your cellphone is equipped with a built-in antenna. For optimal operation, you should

is a registered trademark of Obigo AB.

microSD Logo is a trademark.

The Bluetooth word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by TCT Mobile Limited and its affiliates is under license. Other trademarks and trade names are those of their respective owners

OT-706A Bluetooth QD ID B016328

eZiText™ and Zi™ are trademarks of Zi Corporation and/or 71corporation its Affiliates.

(I) Contact your network operator for service availability

Cellphone warranty.....

Your cellphone is warranted against any defect which may occur in conditions of normal use during the warranty period of twelve (12) months (1) from the date of purchase as shown on your original invoice.

3) Modification or repair performed by individuals not authorized by

• You are advised to switch off the cellphone from time to Batteries (2) and accessories sold with your cellphone are also warranted against any defect which may occur during the first six (6) 4) Inclement weather, lightning, fire, humidity, infiltration of liquids or • You are advised to fully charge (IIII) the battery for optimal months (1) from the date of purchase as shown on your original invoice. In case of any defect of your cellphone which prevents you from normal use thereof, you must immediately inform your vendor and present your cellphone with a proof of purchase.

If the defect is confirmed, your cellphone or part thereof will be either replaced or repaired, as appropriate. Repaired cellphone and accessories are entitled to a one (I) month warranty for the same provided by your jurisdiction. defect. Repair or replacement may be carried out using reconditioned

This warranty shall not apply to defects to your cellphone and/or

accessory due to (without any limitation):

components offering equivalent functionality.

- I) Non-compliance with the instructions for use or installation, or **Troubleshooting......** with technical and safety standards applicable in the geographical area where your cellphone is used 2) Connection to any equipment not supplied or not recommended
- by TCT Mobile Limited.

TCT Mobile Limited or its affiliates or your vendor.

foods, chemical products, download of files, crash, high voltage, corrosion, oxidation...

Your cellphone will not be repaired if case labels or serial numbers (IMEI) have been removed or altered.

There are no express warranties, whether written, oral or implied. other than this printed limited warranty or the mandatory warranty My cellphone will not switch on

In no event shall TCT Mobile Limited or any of its affiliates be liable for incidental or consequential damages of any nature whatsoever, This warranty covers the cost of parts and labor but excludes any including but not limited commercial loss, to the full extent those damages can be disclaimed by law. Some countries/states do not allow My cellphone has not responded for several minutes the exclusion or limitation of incidental or consequential damages, or • Press the 🖭 key limitation of the duration of implied warranties, so the preceding • Remove the battery and re-insert it, then switch the cellphone back limitations or exclusions may not apply to you.

Before contacting the aftersales department, you are advised to follow

• After a partial charge, the battery level indicator may not be exact.

- optimize its performance
- operation
- · Avoid storing large amounts of data in your cellphone as this may affect the performance of your cellphone.

and carry out the following checks:

- Press out until the screen comes on
- · Check the battery charge level
- Check the battery contacts, remove and reinstall your battery, ther turn your cellphone back on

My screen is difficult to read

- Clean your screen
- · Use your cellphone in accordance with the recommended

My cellphone turns off by itself

- · Check that your keypad is locked when you are not using your cellphone
- · Check the hattery charge level

My cellphone has a low level of autonomy

- hours)
- Wait for at least 20 minutes after removing the charger to obtain an valid, etc.) exact indication

My cellphone will not charge properly

- Make sure that your battery is not completely discharged; the The caller's name does not appear when a call is received accompanied by a quiet whistling sound
- Make sure charging is carried out under normal conditions (0°C-
- Make sure your battery is inserted. It must be inserted before
- Make sure you are using an Alcatel battery and charger in the box When abroad, check that the electrical current is compatible

My cellphone will not connect to a network

- Try connecting in another location
- Verify the network coverage with your operator
- Check with your operator that your SIM card is valid Try selecting the available network(s) manually

SIM card error

Make sure the SIM card has been correctly inserted

· Try connecting at a later time if the network is overloaded

- Verify with your operator that your SIM card is 3V or 1.8V compatible; the old 5V SIM cards cannot be used
- Make sure the chip on your SIM card is not damaged or scratched

Unable to make outgoing calls

- Make sure you have dialled a valid number and press the
- For international calls, check the country and area codes Make sure your cellphone is connected to a network and that the
- network is not overloaded or unavailable Check your subscription status with your operator (credit, SIM card
- valid etc) Make sure you have not barred outgoing calls

Unable to receive incoming calls

- Make sure you respected the complete charge timing (minimum 3 Make sure your cellphone is switched on and connected to a network (check for overloaded or unavailable network)
 - · Check your subscription status with your operator (credit, SIM card
 - Make sure you have not forwarded incoming calls
 - Make sure that you have not barred certain calls

battery charge indicator can take several minutes and may be • Check that you have subscribed to this service with your operator Your caller has concealed his/her number

The sound quality of the calls is not optimal

- You can adjust the volume during a call by means of the 💂 key
- Check the network strength 📶
- I am unable to use the features described in the manual
- Check with your operator to make sure that your subscription includes this service
- Make sure this feature does not require an Alcatel accessory

When I select a number from my directory, the number is to reset it (1) not dialled

 Make sure that you have correctly recorded the number in your file Make sure that you have selected the country prefix when calling a

I am unable to create a file in my directory

 Make sure that your SIM card directory is not full; delete some files or save the files in the product directory (i.e. your professional or personal directories)

My callers are unable to leave messages on my voicemail

Contact your network operator to check service availability

Website: www.alcatel-mobilephones.com

Ouestions) section. You can also contact us by e-mail to ask any questions you may have.

An electronic version of this user guide is available in English and other languages according to availability on our server: www.alcatel-

Your cellphone is a transceiver that operates on GSM networks with 850 and 1900 MHz hands

Protection against theft (1)

Your cellphone is identified by an IMEI (cellphone serial number) shown on the packaging label and in the product's memory. We recommend that you note the number the first time you use your cellphone by entering *#06# and keep it in a safe place. It may be requested by the police or your operator if your cellphone is stolen. This number allows your cellphone to be blocked preventing a third person from using it even with a different SIM card

17

There may be certain differences between the user manual description and the cellphone's operation, depending on the software release of your cellphone or specific operator services.

- I cannot access my voicemail Make sure your operator's voicemail number is correctly entered in "My numbers"
- Try later if the network is busy

The | icon is displayed on my standby screen

• You have saved too many short messages on your SIM card: delete some of them or archive them in the product memory

"No service"is displayed You are outside of the network coverage area

I have already entered 3 incorrect PIN codes

 Contact your network operator to obtain the PUK code (Personal) Unblocking Key)

My cellphone is frozen, can't power on

- Make sure your battery is not completely used up or damaged.
- Remove your battery, remove your SIM card then reinstall them to power on again, if still does not work
- Hold down key + y key at same time, then press key

(I) ALL User cellphone data: contacts, photos, messages, files and downloaded applications will be lost permanently. Please do not remove battery during resetting.

(1) The warranty period may vary depending on your country. (2) The life of a rechargeable cellphone battery in terms of

conversation time standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your cellphone during the first six months after purchase and for approximately 200

22

23